



US009271310B2

(12) **United States Patent**  
**Kumar et al.**

(10) **Patent No.:** **US 9,271,310 B2**  
(45) **Date of Patent:** **Feb. 23, 2016**

(54) **METHOD AND APPARATUS FOR A SMART  
RANDOM ACCESS PROCEDURE IN A  
TELECOMMUNICATION NETWORK**

(58) **Field of Classification Search**  
CPC ..... H04L 5/0055  
See application file for complete search history.

(71) Applicant: **QUALCOMM Incorporated**, San Diego, CA (US)  
  
(72) Inventors: **Arvinthan Kumar**, San Diego, CA (US); **Luna Sapna D'Souza**, San Diego, CA (US); **Chetan Gopalakrishnan Chakravarthy**, San Diego, CA (US); **Guruvayurappan Vasudevan**, Hyderabad (IN); **Vaishakh Rao**, San Diego, CA (US)

(56) **References Cited**  
**U.S. PATENT DOCUMENTS**  
  
2010/0182974 A1 7/2010 Barraclough et al.  
2011/0019655 A1 1/2011 Hakola  
2011/0274040 A1 11/2011 Pani et al.  
2012/0250659 A1 10/2012 Sambhwani  
2013/0114518 A1 5/2013 Martin et al.  
2013/0208668 A1 8/2013 Ramos et al.  
2014/0153554 A1\* 6/2014 He et al. .... 370/336  
2014/0286320 A1\* 9/2014 He ..... 370/336

(73) Assignee: **QUALCOMM Incorporated**, San Diego, CA (US)  
  
(\* ) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 140 days.

**FOREIGN PATENT DOCUMENTS**  
  
WO WO-2010124228 A2 10/2010  
WO WO-2013023834 A1 2/2013  
WO WO-2013026184 A1 2/2013

(21) Appl. No.: **14/077,789**  
(22) Filed: **Nov. 12, 2013**

**OTHER PUBLICATIONS**  
  
3GPP TS 25.211: "3rd Generation Partnership Project; Universal Mobile Telecommunications System (UMTS); Physical channels and mapping of transport channels onto physical channels (FDD)," ETSI TS 125 211, Version 8.7.0, Release 8, Oct. 2010, 59 Pages. International Search Report and Written Opinion—PCT/US2014/021257—ISA/EPO—Jun. 3, 2014.

(65) **Prior Publication Data**  
US 2014/0293887 A1 Oct. 2, 2014

\* cited by examiner

**Related U.S. Application Data**

(60) Provisional application No. 61/807,226, filed on Apr. 1, 2013.


*Primary Examiner* — Huy D Vu  
*Assistant Examiner* — Kevin Cunningham  
(74) *Attorney, Agent, or Firm* — Loza & Loza LLP

(51) **Int. Cl.**  
**H04W 4/00** (2009.01)  
**H04W 74/08** (2009.01)  
**H04L 5/00** (2006.01)  
**H04W 72/02** (2009.01)

(57) **ABSTRACT**  
Aspects of the present disclosure provide for a method and an apparatus for wireless communications using an intelligent Random Access Channel (RACH) procedure that may increase the probability of obtaining an available E-DCH resource quickly in a Universal Mobile Telecommunication System.

(52) **U.S. Cl.**  
CPC ..... **H04W 74/0833** (2013.01); **H04L 5/0055** (2013.01); **H04W 72/02** (2013.01)

**24 Claims, 10 Drawing Sheets**






FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6

700 ↙

X = 0	SIG IND = 0, 4	Usable Y, N	Probability
X = 1	SIG IND = 1, 5	Usable Y, N	Probability
X = 2	SIG IND = 2, 6	Usable Y, N	Probability
X = 3	SIG IND = 3, 7	Usable Y, N	Probability




FIG. 7




FIG. 8




FIG. 9




FIG. 10

1

## METHOD AND APPARATUS FOR A SMART RANDOM ACCESS PROCEDURE IN A TELECOMMUNICATION NETWORK

### CROSS-REFERENCE TO RELATED APPLICATIONS

This application claims priority to and the benefit of provisional patent application no. 61/807,226 filed in the United States Patent Office on 1 Apr. 2013, the entire content of which is incorporated herein by reference.

### TECHNICAL FIELD

Aspects of the present disclosure relate generally to wireless communication systems, and more particularly, to a method and apparatus for random access procedure in Universal Mobile Telecommunication System (UMTS).

### BACKGROUND

Wireless communication networks are widely deployed to provide various communication services such as telephony, video, data, messaging, broadcasts, and so on. Such networks, which are usually multiple access networks, support communications for multiple users by sharing the available network resources. One example of such a network is the UMTS Terrestrial Radio Access Network (UTRAN). The UTRAN is the radio access network (RAN) defined as a part of the Universal Mobile Telecommunications System (UMTS), a third generation (3G) mobile phone technology supported by the 3rd Generation Partnership Project (3GPP). UMTS, which is the successor to Global System for Mobile Communications (GSM) technologies, currently supports various air interface standards, such as Wideband-Code Division Multiple Access (W-CDMA), Time Division-Code Division Multiple Access (TD-CDMA), and Time Division-Synchronous Code Division Multiple Access (TD-SCDMA). UMTS also supports enhanced 3G data communications protocols, such as High Speed Packet Access (HSPA), which provides higher data transfer speeds and capacity to associated UMTS networks.

In many wireless networks (e.g., UMTS), a connection between a user equipment (UE) and the network can transition among different states. In UMTS, a UE can transition from a state where a dedicated channel is assigned to the UE to one or more various standby states or an idle state. When the UE transitions to the state to acquire a dedicated channel, the UE may start a random access procedure by randomly selecting an available signature sequence out of a fixed number of sequences, and may transmit a preamble modulated with the selected signature sequence on a physical random access channel (PRACH). However, the randomly selected signature sequence may not always correspond to an available dedicated channel.

As the demand for mobile broadband access continues to increase, research and development continue to advance the UMTS technologies not only to meet the growing demand for mobile broadband access, but to advance and enhance the user experience with mobile communications.

### SUMMARY

The following presents a simplified summary of one or more aspects of the present disclosure, in order to provide a basic understanding of such aspects. This summary is not an extensive overview of all contemplated features of the disclo-

2

sure, and is intended neither to identify key or critical elements of all aspects of the disclosure nor to delineate the scope of any or all aspects of the disclosure. Its sole purpose is to present some concepts of one or more aspects of the disclosure in a simplified form as a prelude to the more detailed description that is presented later.

Aspects of the present disclosure provide for a method and an apparatus for wireless communications using an intelligent Random Access Channel (RACH) procedure that may increase the probability of obtaining an available E-DCH resource quickly.

In one aspect, the disclosure provides a method of operating an apparatus in a wireless communications network. The method includes: creating a database including a plurality of resource indexes and corresponding preamble signature sequences, the resource indexes initially marked as usable and corresponding to a plurality of uplink transport channel resources; selecting a first index of the resource indexes; selecting a first preamble signature sequence of the preamble signature sequences corresponding to the first index; and initiating a random access channel (RACH) procedure by transmitting a preamble utilizing the first preamble signature sequence.

Another aspect of the disclosure provides an apparatus for wireless communications. The apparatus includes: means for creating a database including a plurality of resource indexes and corresponding preamble signature sequences, the resource indexes initially marked as usable and corresponding to a plurality of uplink transport channel resources; means for selecting a first index of the resource indexes; means for selecting a first preamble signature sequence of the preamble signature sequences corresponding to the first index; and means for initiating a random access channel (RACH) procedure by transmitting a preamble utilizing the first preamble signature sequence.

Another aspect of the disclosure provides a computer program product including a computer-readable storage medium. The computer-readable storage medium includes code for causing a user (UE) to: create a database including a plurality of resource indexes and corresponding preamble signature sequences, the resource indexes initially marked as usable and corresponding to a plurality of uplink transport channel resources; select a first index of the resource indexes; select a first preamble signature sequence of the preamble signature sequences corresponding to the first index; and initiate a random access channel (RACH) procedure by transmitting a preamble utilizing the first preamble signature sequence.

Another aspect of the disclosure provides an apparatus for a wireless communications network. The apparatus includes at least one processor, a communication interface coupled to the at least one processor, and a memory coupled to the at least one processor. The at least one processor is configured to: create a database including a plurality of resource indexes and corresponding preamble signature sequences, the resource indexes initially marked as usable and corresponding to a plurality of uplink transport channel resources; select a first index of the resource indexes; select a first preamble signature sequence of the preamble signature sequences corresponding to the first index; and initiate a random access channel (RACH) procedure by transmitting a preamble utilizing the first preamble signature sequence.

These and other aspects of the invention will become more fully understood upon a review of the detailed description, which follows.

### BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram conceptually illustrating an example of a telecommunications system.

FIG. 2 is a conceptual diagram illustrating an example of an access network.

FIG. 3 is a conceptual diagram illustrating an example of a radio protocol architecture for the user and control plane.

FIG. 4 is a state diagram illustrating the operational modes of an UE in a UMTS network as shown in FIG. 1.

FIG. 5 is a conceptual diagram illustrating data transmission for initiating a RACH procedure using an E-DCH in an enhanced Cell\_FACH state.

FIG. 6 is a flow chart illustrating an algorithm for performing an RACH access procedure in accordance with aspects of the present disclosure.

FIG. 7 is a conceptual diagram illustrating a database that may be used in the algorithm of FIG. 6 in accordance with an aspect of the disclosure.

FIG. 8 is a block diagram illustrating an example of a hardware implementation for an apparatus employing a processing system.

FIG. 9 is a conceptual diagram illustrating some functional blocks of a processor and a computer-readable medium in accordance with an aspect of the disclosure.

FIG. 10 is a diagram illustrating a method of operating an apparatus in a wireless communications network in accordance with an aspect of the disclosure.

#### DETAILED DESCRIPTION

The detailed description set forth below in connection with the appended drawings is intended as a description of various configurations and is not intended to represent the only configurations in which the concepts described herein may be practiced. The detailed description includes specific details for the purpose of providing a thorough understanding of various concepts. However, it will be apparent to those skilled in the art that these concepts may be practiced without these specific details. In some instances, well known structures and components are shown in block diagram form in order to avoid obscuring such concepts.

The various concepts presented throughout this disclosure may be implemented across a broad variety of telecommunication systems, network architectures, and communication standards. Referring now to FIG. 1, as an illustrative example without limitation, various aspects of the present disclosure are illustrated with reference to a Universal Mobile Telecommunications System (UMTS) system 100. A UMTS network includes three interacting domains: a core network 104, a radio access network (RAN) (e.g., the UMTS Terrestrial Radio Access Network (UTRAN) 102), and a user equipment (UE) 110. Among several options available for a UTRAN 102, in this example, the illustrated UTRAN 102 may employ a W-CDMA air interface for enabling various wireless services including telephony, video, data, messaging, broadcasts, and/or other services. The UTRAN 102 may include a plurality of Radio Network Subsystems (RNSs) such as an RNS 107, each controlled by a respective Radio Network Controller (RNC) such as an RNC 106. Here, the UTRAN 102 may include any number of RNCs 106 and RNSs 107 in addition to the illustrated RNCs 106 and RNSs 107. The RNC 106 is an apparatus responsible for, among other things, assigning, reconfiguring, and releasing radio resources within the RNS 107. The RNC 106 may be interconnected to other RNCs (not shown) in the UTRAN 102 through various types of interfaces such as a direct physical connection, a virtual network, or the like using any suitable transport network.

The geographic region covered by the RNS 107 may be divided into a number of cells, with a radio transceiver apparatus serving each cell. A radio transceiver apparatus is com-

monly referred to as a Node B in UMTS applications, but may also be referred to by those skilled in the art as a base station (BS), a base transceiver station (BTS), a radio base station, a radio transceiver, a transceiver function, a basic service set (BSS), an extended service set (ESS), an access point (AP), or some other suitable terminology. For clarity, three Node Bs 108 are shown in each RNS 107; however, the RNSs 107 may include any number of wireless Node Bs. The Node Bs 108 provide wireless access points to a core network 104 for any number of mobile apparatuses. Examples of a mobile apparatus include a cellular phone, a smart phone, a session initiation protocol (SIP) phone, a laptop, a notebook, a netbook, a smartbook, a personal digital assistant (PDA), a satellite radio, a global positioning system (GPS) device, a multimedia device, a video device, a digital audio player (e.g., MP3 player), a camera, a game console, or any other similar functioning device. The mobile apparatus is commonly referred to as user equipment (UE) in UMTS applications, but may also be referred to by those skilled in the art as a mobile station (MS), a subscriber station, a mobile unit, a subscriber unit, a wireless unit, a remote unit, a mobile device, a wireless device, a wireless communications device, a remote device, a mobile subscriber station, an access terminal (AT), a mobile terminal, a wireless terminal, a remote terminal, a handset, a terminal, a user agent, a mobile client, a client, or some other suitable terminology. In a UMTS system, the UE 110 may further include a universal subscriber identity module (USIM) 111, which contains a user's subscription information to a network. For illustrative purposes, one UE 110 is shown in communication with a number of the Node Bs 108. The downlink (DL), also called the forward link, refers to the communication link from a Node B 108 to a UE 110 and the uplink (UL), also called the reverse link, refers to the communication link from a UE 110 to a Node B 108.

The core network 104 can interface with one or more access networks, such as the UTRAN 102. As shown, the core network 104 is a UMTS core network. However, as those skilled in the art will recognize, the various concepts presented throughout this disclosure may be implemented in a RAN, or other suitable access network, to provide UEs with access to types of core networks other than UMTS networks.

The illustrated UMTS core network 104 includes a circuit-switched (CS) domain and a packet-switched (PS) domain. Some of the circuit-switched elements are a Mobile services Switching Centre (MSC), a Visitor Location Register (VLR), and a Gateway MSC (GMSC). Packet-switched elements include a Serving GPRS Support Node (SGSN) and a Gateway GPRS Support Node (GGSN). Some network elements, like EIR, HLR, VLR, and AuC may be shared by both of the circuit-switched and packet-switched domains.

In the illustrated example, the core network 104 supports circuit-switched services with a MSC 112 and a GMSC 114. In some applications, the GMSC 114 may be referred to as a media gateway (MGW). One or more RNCs, such as the RNC 106, may be connected to the MSC 112. The MSC 112 is an apparatus that controls call setup, call routing, and UE mobility functions. The MSC 112 also includes a visitor location register (VLR) that contains subscriber-related information for the duration that a UE is in the coverage area of the MSC 112. The GMSC 114 provides a gateway through the MSC 112 for the UE to access a circuit-switched network 116. The GMSC 114 includes a home location register (HLR) 115 containing subscriber data, such as the data reflecting the details of the services to which a particular user has subscribed. The HLR is also associated with an authentication center (AuC) that contains subscriber-specific authentication data. When a call is received for a particular UE, the GMSC

**114** queries the HLR **115** to determine the UE's location and forwards the call to the particular MSC serving that location.

The illustrated core network **104** also supports packet-switched data services with a serving GPRS support node (SGSN) **118** and a gateway GPRS support node (GGSN) **120**. General Packet Radio Service (GPRS) is designed to provide packet-data services at speeds higher than those available with standard circuit-switched data services. The GGSN **120** provides a connection for the UTRAN **102** to a packet-based network **122**. The packet-based network **122** may be the Internet, a private data network, or some other suitable packet-based network. The primary function of the GGSN **120** is to provide the UEs **110** with packet-based network connectivity. Data packets may be transferred between the GGSN **120** and the UEs **110** through the SGSN **118**, which performs primarily the same functions in the packet-based domain as the MSC **112** performs in the circuit-switched domain.

The UTRAN air interface may be a spread spectrum Direct-Sequence Code Division Multiple Access (DS-CDMA) system, such as one utilizing the W-CDMA standards. The spread spectrum DS-CDMA spreads user data through multiplication by a sequence of pseudorandom bits called chips. The W-CDMA air interface for the UTRAN **102** is based on such DS-CDMA technology and additionally calls for a frequency division duplexing (FDD). FDD uses a different carrier frequency for the uplink (UL) and downlink (DL) between a Node B **108** and a UE **110**. Another air interface for UMTS that utilizes DS-CDMA, and uses time division duplexing (TDD), is the TD-SCDMA air interface. Those skilled in the art will recognize that although various examples described herein may refer to a W-CDMA air interface, the underlying principles are equally applicable to a TD-SCDMA air interface or any other suitable air interface.

The UTRAN **102** is one example of a RAN that may be utilized in accordance with the present disclosure. Referring to FIG. 2, by way of example and without limitation, a simplified schematic illustration of a RAN **200** in a UTRAN architecture is illustrated. The system includes multiple cellular regions (cells), including cells **202**, **204**, and **206**, each of which may include one or more sectors. Cells may be defined geographically (e.g., by coverage area) and/or may be defined in accordance with a frequency, scrambling code, etc. That is, the illustrated geographically-defined cells **202**, **204**, and **206** may each be further divided into a plurality of cells, e.g., by utilizing different scrambling codes. For example, cell **204a** may utilize a first scrambling code, and cell **204b**, while in the same geographic region and served by the same Node B **244**, may be distinguished by utilizing a second scrambling code.

In a cell that is divided into sectors, the multiple sectors within a cell can be formed by groups of antennas with each antenna responsible for communication with UEs in a portion of the cell. For example, in cell **202**, antenna groups **212**, **214**, and **216** may each correspond to a different sector. In cell **204**, antenna groups **218**, **220**, and **222** may each correspond to a different sector. In cell **206**, antenna groups **224**, **226**, and **228** may each correspond to a different sector.

The cells **202**, **204**, and **206** may include several UEs that may be in communication with one or more sectors of each cell **202**, **204**, or **206**. For example, UEs **230** and **232** may be in communication with Node B **242**, UEs **234** and **236** may be in communication with Node B **244**, and UEs **238** and **240** may be in communication with Node B **246**. Here, each Node B **242**, **244**, and **246** may be configured to provide an access point to a core network **204** (see FIG. 2) for all the UEs **230**, **232**, **234**, **236**, **238**, and **240** in the respective cells **202**, **204**, and **206**.

During a call with a source cell, or at any other time, the UE **236** may monitor various parameters of the source cell as well as various parameters of neighboring cells. Further, depending on the quality of these parameters, the UE **236** may maintain communication with one or more of the neighboring cells. During this time, the UE **236** may maintain an Active Set, that is, a list of cells to which the UE **236** is simultaneously connected (i.e., the UTRAN cells that are currently assigning a downlink dedicated physical channel DPCH or fractional downlink dedicated physical channel F-DPCH to the UE **236** may constitute the Active Set).

A high speed packet access (HSPA) air interface includes a series of enhancements to the 3G/W-CDMA air interface between the UE **110** and the UTRAN **102**, facilitating greater throughput and reduced latency for users. Among other modifications over prior standards, HSPA utilizes hybrid automatic repeat request (HARQ), shared channel transmission, and adaptive modulation and coding. The standards that define HSPA include HSDPA (high speed downlink packet access) and HSUPA (high speed uplink packet access, also referred to as enhanced uplink or EUL). In HSUPA, the Enhanced Dedicated Channel (E-DCH) may be used to carry user data in the uplink direction. The E-DCH transport channel includes two channels: E-DPDCH to carry user data and E-DPCCH to carry the physical layer uplink control information.

In a wireless telecommunication system, the communication protocol architecture may take on various forms depending on the particular application. For example, in a 3GPP UMTS system, the signaling protocol stack is divided into a Non-Access Stratum (NAS) and an Access Stratum (AS). The NAS provides the upper layers, for signaling between the UE **110** and the core network **104** (referring to FIG. 1), and may include circuit switched and packet switched protocols. The AS provides the lower layers, for signaling between the UTRAN **102** and the UE **110**, and may include a user plane and a control plane. Here, the user plane or data plane carries user traffic, while the control plane carries control information (i.e., signaling).

Turning to FIG. 3, the AS is shown with three layers: Layer 1, Layer 2, and Layer 3. Layer 1 is the lowest layer and implements various physical layer signal processing functions. Layer 1 will be referred to herein as the physical layer **306**. The data link layer, called Layer 2 **308**, is above the physical layer **306** and is responsible for the link between the UE **110** and Node B **108** over the physical layer **306**.

At Layer 3, the RRC layer **316** handles the control plane signaling between the UE **110** and the Node B **108**. RRC layer **316** includes a number of functional entities for routing higher layer messages, handling broadcasting and paging functions, establishing and configuring radio bearers, etc.

In the illustrated air interface, the L2 layer **308** is split into sublayers. In the control plane, the L2 layer **308** includes two sublayers: a medium access control (MAC) sublayer **310** and a radio link control (RLC) sublayer **312**. In the user plane, the L2 layer **308** additionally includes a packet data convergence protocol (PDCP) sublayer **314**. Although not shown, the UE may have several upper layers above the L2 layer **308** including a network layer (e.g., IP layer) that is terminated at a PDN gateway on the network side and an application layer that is terminated at the other end of the connection (e.g., far end UE, server, etc.).

The PDCP sublayer **314** provides multiplexing between different radio bearers and logical channels. The PDCP sublayer **314** also provides header compression for upper layer

data packets to reduce radio transmission overhead, security by ciphering the data packets, and handover support for UEs between Node Bs.

The RLC sublayer **312** generally supports an acknowledged mode (AM) (where an acknowledgment and retransmission process may be used for error correction), an unacknowledged mode (UM), and a transparent mode for data transfers, and provides segmentation and reassembly of upper layer data packets and reordering of data packets to compensate for out-of-order reception due to a hybrid automatic repeat request (HARQ) at the MAC layer. In the acknowledged mode, RLC peer entities such as an RNC and a UE may exchange various RLC protocol data units (PDUs) including RLC Data PDUs, RLC Status PDUs, and RLC Reset PDUs, among others. In the present disclosure, the term “packet” may refer to any RLC PDU exchanged between RLC peer entities.

The MAC sublayer **310** provides multiplexing between logical and transport channels. The MAC sublayer **310** is also responsible for allocating the various radio resources (e.g., resource blocks) in one cell among the UEs. The MAC sublayer **310** is also responsible for HARQ operations. In HSUPA, both the UE and the RNC include additional MAC functionalities. For example, on the UE side, the new functionality represents the uplink scheduling and retransmission handling (being controlled by the MAC-e in Node B). The MAC-es functionality in the RNC is to cover for packet reordering to avoid changes to the layers above. This reordering is needed because the packets may arrive out of sequence from different base stations.

FIG. 4 is a state diagram illustrating the operational modes of the UE **110** in, for example, the UMTS network **100** as described above. Two basic operational modes of the UE **110** are idle mode and connected mode. The connected mode can be further divided into a number of service states, which define what kind of physical channels the UE **110** is using. FIG. 4 shows the main RRC service states in the connected mode. It also shows the transitions between an idle mode **400** and a connected mode **402** and the possible transitions within the connected mode. In the idle mode **400**, the UE **110** is able to receive system information and cell broadcast (CB) messages. The UE **110** stays in the idle mode **400** until it transmits a request to establish an RRC connection. In the idle mode **400**, the UTRAN **102** has no information of its own about the individual idle-mode UEs and can only address, for example, all UEs in a cell or all UEs monitoring a paging occasion.

In the connected mode **402**, the UE **110** may be in one of a Cell\_DCH state **404**, a Cell\_FACH state **406**, a Cell\_PCH state **408**, and a URA\_PCH state **410**. In the Cell\_DCH state **404**, a dedicated physical channel is allocated to the UE **110**, and the UE **110** is known by its serving RNC on a cell or active set level. In the Cell\_FACH state **406**, no dedicated physical channel is allocated for the UE **110**, but random access channels (RACHs) and forward access channels (FACHs) are used instead, for transmitting both signaling messages and small amounts of user-plane data. The UE’s power consumption is typically less in the Cell\_FACH state **406** than that of the Cell\_DCH state **404**.

In the Cell\_PCH state **410**, the UE **110** is still known on a cell level in the serving RNC (SRNC), but it can be reached only via the paging channel (PCH). In this state, the UE’s battery consumption is less than that of the Cell\_DCH state **404** and/or the Cell\_FACH state **406** since the monitoring of the PCH includes a discontinuous reception (DRX) functionality. If the UE **110** performs a cell reselection, then it moves autonomously to the Cell\_FACH state **406** to execute the Cell Update procedure, after which it re-enters the Cell\_PCH state

**410** if no other activity is triggered during the Cell Update procedure. If a new cell is selected from another radio access system, then the RRC state is changed to the idle mode **400** and access to the other system is performed according to that system’s specifications.

The URA\_PCH state **410** is very similar to the Cell\_PCH state **408**, except that the UE **110** does not execute Cell Update after each cell reselection, but instead reads UTRAN Registration Area (URA) identities from the BCH, and only if the URA changes (after cell reselection) does the UE **110** inform its location to the SRNC. The power consumption of the UE **110** is typically less in the URA\_PCH state **408** than that of the Cell\_DCH state **404** and/or the Cell\_FACH state **406**.

The UE **110** leaves the connected mode and returns to the idle mode **400** when the RRC connection is released or at RRC connection failure. Transitioning the UE **110** among the above states involves exchanging control messages on the control channels. For example, the UE **110** can send a signaling connection release indication (SCRI) to the RNC **106**. Based on the values of the received SCRI, the RNC **106** may command the UE **110** to use the Cell\_PCH state **408** or the URA\_PCH state **410**, instead of releasing the RRC connection and dropping the UE **110** into the idle mode **400**. In another example, the RNC **106** can command the UE **110** to drop to the idle mode **400** directly from the Cell\_DCH state **404**.

In the idle mode **400**, the UE **110** can transition to the Cell\_DCH state **404** or Cell\_FACH state **406**. This transition from the idle mode **400** is initiated by an RRC connection request. This step involves setting up the necessary radio access bearers (RABs). Transitions from the Cell\_FACH state **406** or Cell\_DCH state **404** to the Cell\_PCH state **408** involves tearing down radio access bearers that have been allocated. A transition from the Cell\_DCH state **404** to the Cell\_FACH state **406** involves withdrawing the power and code allocated. When the UE **110** is in the Cell\_DCH state **404**, the UE **110** consumes more energy than the other states to keep the connection going in the DCH state.

In many wireless networks (e.g., UMTS), a connection can be transitioned from the Cell\_DCH state **404** to the Cell\_FACH state **406** to reduce power consumption under certain conditions, but data throughput in the Cell\_FACH state **406** is lower than that of the Cell\_DCH state **404**. However, the amount of energy required on the UE’s side can still be significant in the Cell\_FACH state **406**. Therefore, the UE **110** can be transitioned from the Cell\_DCH state **404** and Cell\_FACH **406** to an even lower energy consuming state, such as the Cell\_PCH state **408**, the URA\_PCH state **410**, or back to the idle mode **400**.

The 3GPP Specification Release 7 and Release 8 introduced the Enhanced Cell\_FACH state to improve the end user performance and system efficiency by utilizing HSPA transport and physical channels in the Cell\_FACH state. The state transition from Enhanced Cell\_FACH (hereafter may be referred to as “Cell\_FACH”) to Cell\_DCH is practically seamless because the physical channel is not changed. In the Cell\_FACH state, the E-DCH transport channel is used for uplink transmission. E-DCH resources and initial data rate allocation to be used in the Cell\_FACH state are broadcast to the cell.

FIG. 5 is a conceptual diagram illustrating data transmission for initiating a RACH procedure using an E-DCH in the Enhanced Cell\_FACH state. In a UMTS system **100**, a UE **110** starts a RACH procedure to initiate uplink transmission. The RACH is typically used for signaling purposes, to register the UE **110** after power-on to the network or to perform

location update after moving from one location area to another or to initiate a call. To initiate the RACH procedure, the UE 110 randomly selects an available signature sequence and transmits one or more preambles 502 modulated with the selected signature sequence on a physical random access channel (PRACH). For example, sixteen signature sequences have been specified for RACH use in the UMTS standards. The preambles are sent prior to data transmission. These use a spreading factor of 256 and contain a signature sequence of 16 symbols, resulting in a total length of 4096 chips for the preamble. The UE 110 decodes an Acquisition Indicator Channel (AICH) to determine whether a base station has detected the preamble 502. When the network detects the preamble 502, an AICH preamble 503 is transmitted on the AICH. The AICH carries Acquisition Indicators (AI) that correspond to signatures on the PRACH. The AICH uses an identical signature sequence as the RACH on one of the downlink channelization codes of the base station to which the RACH belongs. Once the base station has detected the preamble with the random access attempt, then the same signature sequence that has been used on the preamble will be echoed back on AICH. At the point of preamble acquisition 504, a Node B 108 points the UE 110 to a specific E-DCH resource with AICH. At the time point 506, the UE 110 may end data transmission or moves to the Cell\_DCH state to continue data transmission.

With enhanced Cell\_FACH in UL (a.k.a. HSRACH), the network may allocate a subset of the sixteen available RACH signature sequences dedicated for HSUPA users in the enhanced Cell\_FACH state. The network also allocates "Y" number of common E-DCH resources (e.g., E-DCH channels) for such enhanced UL users in the Cell\_FACH state. Without the availability of an enhanced AICH (E-AICH) configuration, the network can only assign a default common E-DCH resource index for a user. For more detail, see 3GPP specification 25.211, which is incorporated herein in its entirety. The association between the Acquisition Indicator of the AICH and the default E-DCH resource index is defined by equation (1) below.

$$X = \text{SigInd} \bmod Y \quad (1)$$

In equation (1), X is the default E-DCH resource index, Y is the total number of E-DCH resources configured in the cell for UL use in the Enhanced Cell\_FACH state and Idle mode, and SigInd is the signature index corresponding to the PRACH preamble signature (indicated by AI) that is configured to be available in the cell and corresponding to E-DCH transmission for Enhanced Uplink in Cell\_FACH state and Idle mode, counting from zero and taking into account only the PRACH preamble signature indexes that are configured available in the cell and corresponding to E-DCH transmission for Enhanced Uplink in Cell\_FACH state and Idle mode.

The above equation (1) ties the available signatures for HS-RACH users to a particular common E-DCH resource index. While a UE 110 starts a RACH procedure, it picks an RACH preamble signature sequence randomly from the available ones. As such, every signature sequence has an equal probability to be selected by the UE at a given instant, and the probability of the UE selecting an available common E-DCH resource from the network can be represented as a ratio defined by equation (2).

$$\frac{\text{Number of signatures for that particular resource}}{\text{Number of available signatures}} \quad (2)$$

In some scenarios, the common E-DCH resource selected by the signature index may not be available. Therefore, this

may potentially delay the probability of getting an available common E-DCH resource from the network, as the RACH preamble signatures are picked randomly with equal probability.

Aspects of the present disclosure provide an intelligent random access channel (RACH) procedure in Enhanced Cell\_FACH. Instead of selecting the RACH preamble signature randomly, a UE 110 maintains a database of available common E-DCH resources and the set of RACH preamble signature sequences that are tied to each of the E-DCH resources.

FIG. 6 is a flow chart illustrating an algorithm 600 for performing an RACH access procedure in accordance with aspects of the present disclosure. The algorithm 600 may be performed using the UE 110 with the UTRAN 102 (see FIG. 1). Referring to FIG. 6, in step 602, the UE 110 operable in a wireless communications network (e.g., UMTS system 100) is configured to create a database that contains information pertaining to common E-DCH resources available for HSRACH users and their corresponding RACH signature sequences. FIG. 7 is a conceptual diagram illustrating a database 700 that may be used in the algorithm 600 in accordance with an aspect of the disclosure. In this example, four common E-DCH resources (denoted as X=0, 1, 2, or 3) are allocated for HSRACH users. Each of the E-DCH 702 resources is mapped to a corresponding preamble signature index (SIG IND) 704. Here, each of the signature indexes denotes a corresponding RACH signature sequence. In this example, the E-DCH resource X=0 is mapped to the signature indexes 0 and 4; the E-DCH resource X=1 is mapped to the signature indexes 1 and 5; the E-DCH resource X=2 is mapped to the signature indexes 2 and 6; and the E-DCH resource X=3 is mapped to the signature indexes 3 and 7. Each of the E-DCH resources in the database 700 is marked as usable or not usable and has a corresponding probability of being usable. At the beginning of the process 600, the E-DCH resources may have the same probability as one another in the database 700. In other aspects of the disclosure, the network may assign different numbers of E-DCH resources for different HSRACH users, and the E-DCH resources may have the same number or different numbers of corresponding signatures.

In step 604, if the UE 110 initiates a RACH procedure, it proceeds to step 606. In step 606, the UE 110 randomly selects a common E-DCH resource index (e.g., X=0) that is marked unused based on its corresponding probability. For example, the UE 110 may select an unused E-DCH resource index in the database having a higher probability. Initially, all the E-DCH resource indexes are marked as unused (i.e., Usable=Yes) in the database 700. In step 608, the UE 110 randomly selects a signature sequence index (e.g., SIG IND=4) from the list of signature sequences (e.g., SIGN IND=0, 4) that are mapped to the selected common E-DCH resource index. Then the UE 110 requests access to the network by sending a RACH preamble (e.g., preamble 502) with the selected signature sequence.

In step 610, the UE 110 monitors the Acquisition Indicator Channel (AICH) to determine whether or not the RACH preamble is acknowledged by the network. If an Acknowledgement message (ACK) is received from the network, the RACH procedure ends in step 612, and the UE 110 may use the selected E-DCH resources to access the network. If no ACK is received from the network for the RACH preamble transmission, the UE 110 marks the selected common E-DCH resource index as unusable or used (i.e., Usable=N) in the database in step 614. For the next RACH preamble attempt, the UE 110 will select another common E-DCH resource

## 11

index randomly excluding the ones already selected that are flagged as unusable in the database 700.

In step 616, the UE 110 checks whether or not the maximum number of RACH attempts is reached. In one example, the maximum number of RACH attempts may be any suitable value from 1 to 64, which is configured by the network. If the maximum number is reached, the UE 110 ends the RACH procedure in step 612 and resets all the E-DCH resource indexes as usable in the database. If the maximum number is not reached yet, the UE 110 checks whether or not all E-DCH indexes are marked as used in step 618. If all of the E-DCH resource indexes are marked as used (i.e., Usable=N), the UE 110 resets or marks all of the E-DCH indexes as unused (i.e., Usable=Y) again in step 620. Here, when each E-DCH resource index is used at least once, all of the indexes will be marked as used in the database 700, and their corresponding probabilities are reset. In one example, the initial probability may be reset to be the same for all indices.

Returning to step 610, if the UE 110 receives a Negative Acknowledgement message (NACK) from the network, the UE 110 performs a typical RACH backoff procedure in step 622 and marks this E-DCH index with a lower probability in the database 700 for the subsequent RACH procedure. In a typical RACH backoff, the UE 110 determines a suitable wait period and delays transmission of a subsequent access attempt signal for the wait period in response to an unsuccessful access attempt to the RACH. By performing the RACH procedure with the above-described algorithm 600, the procedure intelligently selects the common E-DCH resources that may increase or maximize the probability of getting an available E-DCH resource quickly.

FIG. 8 is a conceptual diagram illustrating an example of a hardware implementation for an apparatus 800 employing a processing system 814. In aspects of the disclosure, the apparatus 800 may be implemented as the UE 110 configured to perform the algorithm 600 as described above in reference to FIGS. 6 and 7. In accordance with various aspects of the disclosure, an element, or any portion of an element, or any combination of elements may be implemented with a processing system 814 that includes one or more processors 804. Examples of processors 804 include microprocessors, microcontrollers, digital signal processors (DSPs), field programmable gate arrays (FPGAs), programmable logic devices (PLDs), state machines, gated logic, discrete hardware circuits, and other suitable hardware configured to perform the various functionality described throughout this disclosure.

In this example, the processing system 814 may be implemented with a bus architecture, represented generally by the bus 802. The bus 802 may include any number of interconnecting buses and bridges depending on the specific application of the processing system 814 and the overall design constraints. The bus 802 links together various circuits including one or more processors (represented generally by the processor 804), a memory 805, and computer-readable media (represented generally by the computer-readable storage medium 806). The bus 802 may also link various other circuits such as timing sources, peripherals, voltage regulators, and power management circuits, which are well known in the art, and therefore, will not be described any further. A bus interface 808 provides an interface between the bus 802 and a communication interface (e.g., transceiver 810). The transceiver 810 provides a means for communicating with various other apparatus over a transmission medium. Depending upon the nature of the apparatus, a user interface 812 (e.g., keypad, display, speaker, microphone, joystick, touchscreen, touchpad) may also be provided.

## 12

The processor 804 is responsible for managing the bus 802 and general processing, including the execution of software stored on the computer-readable medium 806. The software, when executed by the processor 804, causes the processing system 814 to perform the various functions described in FIGS. 6 and 7 for the UE 110. For example, the software may include a smart RACH software 807 for causing various components and circuitry of the processor 804 to execute the algorithm 600 described above. The computer-readable medium 806 may also be used for storing data (e.g., database 700) that is manipulated by the processor 804 when executing software.

One or more processors 804 in the processing system may execute software. Software shall be construed broadly to mean instructions, instruction sets, code, code segments, program code, programs, subprograms, software modules, applications, software applications, software packages, routines, subroutines, objects, executables, threads of execution, procedures, functions, etc., whether referred to as software, firmware, middleware, microcode, hardware description language, or otherwise. The software may reside on a computer-readable medium 806. The computer-readable medium 806 may be a non-transitory computer-readable medium. A non-transitory computer-readable medium includes, by way of example, a magnetic storage device (e.g., hard disk, floppy disk, magnetic strip), an optical disk (e.g., a compact disc (CD) or a digital versatile disc (DVD)), a smart card, a flash memory device (e.g., a card, a stick, or a key drive), a random access memory (RAM), a read only memory (ROM), a programmable ROM (PROM), an erasable PROM (EPROM), an electrically erasable PROM (EEPROM), a register, a removable disk, and any other suitable medium for storing software and/or instructions that may be accessed and read by a computer. The computer-readable medium 806 may reside in the processing system 814, external to the processing system 814, or distributed across multiple entities including the processing system 814. The computer-readable medium 806 may be embodied in a computer program product. By way of example, a computer program product may include a computer-readable medium in packaging materials. Those skilled in the art will recognize how best to implement the described functionality presented throughout this disclosure depending on the particular application and the overall design constraints imposed on the overall system.

FIG. 9 is a conceptual diagram illustrating some functional blocks of a processor 900 and a computer-readable medium 910 in accordance with an aspect of the disclosure. The processor 900 may be the same as the processor 804, and the computer-readable medium 910 may be the same as the computer-readable medium 806. The processor 900 includes database handling circuitry 902, resource index selection circuitry 904, preamble signature sequence selection circuitry 906, and RACH handling circuitry 908. The computer-readable medium 910 includes a database handling routine 912, a resource index selection routine 914, a preamble signature sequence selection routine 916, and a RACH handling routine 918. The database handling circuitry 902 when configured by the database handling routine 912, can create a database 920 including a number of resource indexes and corresponding preamble signature sequences. The database 920 may be the same as the database 700. The resource indexes are initially marked as usable and correspond to a plurality of uplink transport channel resources. In an aspect of the disclosure, the uplink transport channel resources may be E-DCH resources. The resource index selection circuitry 904 when configured by the resource index selection routine 914, can select a first index (e.g., index X 702) of the resource

indexes. The preamble signature sequence selection circuitry **906** when configured by the preamble signature sequence selection routine **916**, can select a first preamble signature sequence (e.g., SIG IND **704**) of the preamble signature sequences corresponding to the first index. The RACH handling circuitry **908** when configured by the RACH handling routine **918**, can initiate an RACH procedure by transmitting a preamble utilizing the first preamble signature sequence. In addition, the various functional blocks of the processor **900** and computer-readable medium **910** may be used to perform the various functionalities described in reference to FIGS. **5-7**.

FIG. **10** is a block diagram illustrating a method **1000** of operating an apparatus in a wireless communications network in accordance with an aspect of the disclosure. The apparatus may be the UE **110**. In step **1002**, the apparatus creates a database including a number of resource indexes and corresponding preamble signature sequences, the resource indexes initially marked as usable and corresponding to a plurality of uplink transport channel resources. For example, the resource indexes may be the E-DCH resource indexes ( $X=0, 1, 2, \text{ or } 3$ ) in the database **700**. The apparatus may include the processor **900** that executes the database handling routine **912** to configure the database handling circuitry **902** to perform, for example, the functionalities of step **1002**. In step **1004**, the apparatus selects a first index of the resource indexes. For example, the processor **900** of the apparatus executes the resource index selection routine **914** to configure the resource index selection circuitry **904** to perform, for example, the functionalities of step **1004**. In step **1006**, the apparatus selects a first preamble signature sequence of the preamble signature sequences corresponding to the first index. For example, the preamble signature sequences correspond to the SIG INDS in the database **700**. The processor **900** of the apparatus may execute the preamble signature sequence selection routine **916** to configure the preamble signature sequence selection circuitry **906** to perform, for example, the functionalities of step **1006**. In step **1008**, the apparatus initiates a random access channel (RACH) procedure by transmitting a preamble (e.g., preamble **502**) utilizing the first preamble signature sequence. The processor **900** of the apparatus may execute the RACH handling routine **918** to configure the RACH handling circuitry **908** to perform, for example, the functionalities of step **1008**.

Several aspects of a telecommunications system have been presented with reference to a W-CDMA system. As those skilled in the art will readily appreciate, various aspects described throughout this disclosure may be extended to other telecommunication systems, network architectures and communication standards.

By way of example, various aspects may be extended to other UMTS systems such as TD-SCDMA and TD-CDMA. Various aspects may also be extended to systems employing Long Term Evolution (LTE) (in FDD, TDD, or both modes), LTE-Advanced (LTE-A) (in FDD, TDD, or both modes), CDMA2000, Evolution-Data Optimized (EV-DO), Ultra Mobile Broadband (UMB), IEEE 802.11 (Wi-Fi), IEEE 802.16 (WiMAX), IEEE 802.20, Ultra-Wideband (UWB), Bluetooth, and/or other suitable systems. The actual telecommunication standard, network architecture, and/or communication standard employed will depend on the specific application and the overall design constraints imposed on the system.

It is to be understood that the specific order or hierarchy of steps in the methods disclosed is an illustration of exemplary processes. Based upon design preferences, it is understood that the specific order or hierarchy of steps in the methods

may be rearranged. The accompanying method claims present elements of the various steps in a sample order, and are not meant to be limited to the specific order or hierarchy presented unless specifically recited therein.

The previous description is provided to enable any person skilled in the art to practice the various aspects described herein. Various modifications to these aspects will be readily apparent to those skilled in the art, and the generic principles defined herein may be applied to other aspects. Thus, the claims are not intended to be limited to the aspects shown herein, but are to be accorded the full scope consistent with the language of the claims, wherein reference to an element in the singular is not intended to mean "one and only one" unless specifically so stated, but rather "one or more." Unless specifically stated otherwise, the term "some" refers to one or more. A phrase referring to "at least one of" a list of items refers to any combination of those items, including single members. As an example, "at least one of: a, b, or c" is intended to cover: a; b; c; a and b; a and c; b and c; and a, b and c. All structural and functional equivalents to the elements of the various aspects described throughout this disclosure that are known or later come to be known to those of ordinary skill in the art are expressly incorporated herein by reference and are intended to be encompassed by the claims. Moreover, nothing disclosed herein is intended to be dedicated to the public regardless of whether such disclosure is explicitly recited in the claims. No claim element is to be construed under the provisions of 35 U.S.C. §112, sixth paragraph, unless the element is expressly recited using the phrase "means for" or, in the case of a method claim, the element is recited using the phrase "step for."

What is claimed is:

1. A method of operating an apparatus in a wireless communications network, comprising:
  - creating a database comprising a plurality of resource indexes and corresponding preamble signature sequences and probabilities of being usable, the resource indexes initially marked as usable and corresponding to a plurality of uplink transport channel resources;
  - selecting a first index of the resource indexes;
  - selecting a first preamble signature sequence of the preamble signature sequences corresponding to the first index;
  - initiating a random access channel (RACH) procedure by transmitting a preamble utilizing the first preamble signature sequence;
  - marking the first index with a lower probability of being usable for a subsequent RACH procedure in connection with receiving a negative acknowledgement for the preamble;
  - selecting a second index of the resource indexes having a probability higher than that of the first index;
  - if no acknowledgement is received from the wireless communications network for the preamble, marking the first index as unusable in the database;
  - selecting a second preamble signature sequence of the preamble signature sequences corresponding to the second index; and
  - transmitting a preamble utilizing the second preamble signature sequence.
2. The method of claim 1, wherein the uplink transport channel resources comprise a plurality of Enhanced Dedicated Channel (E-DCH) resources.

## 15

3. The method of claim 1, further comprising:  
if the database comprises at least one index marked as usable among the resource indexes, selecting a third index of the at least one usable index;  
selecting a third preamble signature sequence of the preamble signature sequences corresponding to the third index; and  
transmitting a preamble utilizing the third preamble signature sequence.

4. The method of claim 1, further comprising:  
if the database comprises no index marked as usable among the resource indexes, marking all of the resource indexes as usable.

5. The method of claim 1, further comprising:  
receiving a negative acknowledgement for the preamble;  
and  
performing a backoff procedure of the RACH procedure.

6. The method of claim 1, wherein the selecting the first index comprises randomly selecting an index marked as usable from among the resource indexes.

7. An apparatus for wireless communications, comprising:  
means for creating a database comprising a plurality of resource indexes and corresponding preamble signature sequences and probabilities of being usable, the resource indexes initially marked as usable and corresponding to a plurality of uplink transport channel resources;

means for selecting a first index of the resource indexes;  
means for selecting a first preamble signature sequence of the preamble signature sequences corresponding to the first index;

means for initiating a random access channel (RACH) procedure by transmitting a preamble utilizing the first preamble signature sequence;

means for marking the first index with a lower probability of being usable for a subsequent RACH procedure in connection with receiving a negative acknowledgement for the preamble;

means for selecting a second index of the resource indexes having a probability higher than that of the first index;  
means for if no acknowledgement is received for the preamble, marking the first index as unusable in the database;

means for selecting a second preamble signature sequence of the preamble signature sequences corresponding to the second index; and

means for transmitting a preamble utilizing the second preamble signature sequence.

8. The apparatus of claim 7, wherein the uplink transport channel resources comprise a plurality of Enhanced Dedicated Channel (E-DCH) resources.

9. The apparatus of claim 7, further comprising:  
if the database comprises at least one index marked as usable among the resource indexes, means for selecting a third index of the at least one usable index;

means for selecting a third preamble signature sequence of the preamble signature sequences corresponding to the third index; and

means for transmitting a preamble utilizing the third preamble signature sequence.

10. The apparatus of claim 7, further comprising:  
if the database comprises no index marked as usable among the resource indexes, means for marking all of the resource indexes as usable.

## 16

11. The apparatus of claim 7, further comprising:  
means for receiving a negative acknowledgement for the preamble;  
and  
means for performing a backoff procedure of the RACH procedure.

12. The apparatus of claim 7, wherein the selecting the first index comprises means for randomly selecting an index marked as usable from among the resource indexes.

13. A non-transitory computer-readable storage medium comprising:

code for causing a user equipment (UE) to:  
create a database comprising a plurality of resource indexes and corresponding preamble signature sequences and probabilities of being usable, the resource indexes initially marked as usable and corresponding to a plurality of uplink transport channel resources;

select a first index of the resource indexes;  
select a first preamble signature sequence of the preamble signature sequences corresponding to the first index;  
initiate a random access channel (RACH) procedure by transmitting a preamble utilizing the first preamble signature sequence;

mark the first index with a lower probability of being usable for a subsequent RACH procedure in connection with receiving a negative acknowledgement for the preamble;

select a second index of the resource indexes having a probability higher than that of the first index;  
if no acknowledgement is received for the preamble, mark the first index as unusable in the database;

select a second preamble signature sequence of the preamble signature sequences corresponding to the second index; and

transmit a preamble utilizing the second preamble signature sequence.

14. The non-transitory computer-readable storage medium of claim 13, wherein the uplink transport channel resources comprise a plurality of Enhanced Dedicated Channel (E-DCH) resources.

15. The non-transitory computer-readable storage medium of claim 13, further comprising code for causing the UE to:  
if the database comprises at least one index marked as usable among the resource indexes, select a third index of the at least one usable index;

select a third preamble signature sequence of the preamble signature sequences corresponding to the third index;  
and

transmit a preamble utilizing the third preamble signature sequence.

16. The non-transitory computer-readable storage medium of claim 13, further comprising code for causing the UE to:  
if the database comprises no index marked as usable among the resource indexes, mark all of the resource indexes as usable.

17. The non-transitory computer-readable storage medium of claim 13, further comprising code for causing the UE to:  
receive a negative acknowledgement for the preamble;  
and  
perform a backoff procedure of the RACH procedure.

18. The non-transitory computer-readable storage medium of claim 13, further comprising code for causing the UE to:  
randomly select an index marked as usable from among the resource indexes.

17

19. An apparatus for a wireless communications network, comprising:  
 at least one processor;  
 a communication interface coupled to the at least one processor; and  
 a memory coupled to the at least one processor,  
 wherein the at least one processor is configured to:  
 create a database comprising a plurality of resource indexes and corresponding preamble signature sequences and probabilities of being usable, the resource indexes initially marked as usable and corresponding to a plurality of uplink transport channel resources;  
 select a first index of the resource indexes;  
 select a first preamble signature sequence of the preamble signature sequences corresponding to the first index;  
 initiate a random access channel (RACH) procedure by transmitting a preamble utilizing the first preamble signature sequence;  
 mark the first index with a lower probability of being usable for a subsequent RACH procedure in connection with receiving a negative acknowledgement for the preamble;  
 select a second index of the resource indexes having a probability higher than that of the first index;  
 if no acknowledgement is received from the wireless communications network for the preamble, mark the first index as unusable in the database;  
 select a second preamble signature sequence of the preamble signature sequences corresponding to the second index; and

18

transmit a preamble utilizing the second preamble signature sequence.  
 20. The apparatus of claim 19, wherein the uplink transport channel resources comprise a plurality of Enhanced Dedicated Channel (E-DCH) resources.  
 21. The apparatus of claim 19, wherein the at least one processor is further configured to:  
 if the database comprises at least one index marked as usable among the resource indexes, select a third index of the at least one usable index;  
 select a third preamble signature sequence of the preamble signature sequences corresponding to the third index; and  
 transmit a preamble utilizing the third preamble signature sequence.  
 22. The apparatus of claim 19, wherein the at least one processor is further configured to:  
 if the database comprises no index marked as usable among the resource indexes, mark all of the resource indexes as usable.  
 23. The apparatus of claim 19, wherein the at least one processor is further configured to:  
 receive a negative acknowledgement for the preamble; and  
 perform a backoff procedure of the RACH procedure.  
 24. The apparatus of claim 19, wherein for selecting the first index, the at least one processor is further configured to randomly select an index marked as usable from among the resource indexes.

\* \* \* \* \*